



# **HIGH-RESOLUTION IMAGING**

**DETECTORS AND APPLICATIONS**

Swapan K. Saha



The background features a dark grey field with numerous small, bright white stars of varying sizes. A horizontal line of four circular images is positioned in the upper half of the frame. From left to right, these circles show a progression of image quality: the first is very noisy and blurry; the second is slightly clearer but still noisy; the third is sharper with a small white triangle pointing to a specific feature; the fourth is the sharpest, showing a clear central bright spot. In the lower-left quadrant, there is a bright, multi-pointed starburst or lens flare effect. The text 'HIGH-RESOLUTION IMAGING' is centered in the lower half of the image.

# **HIGH-RESOLUTION IMAGING**



# **HIGH-RESOLUTION IMAGING**

**DETECTORS AND APPLICATIONS**

Swapan K. Saha

PAN STANFORD  PUBLISHING

CRC Press  
Taylor & Francis Group  
6000 Broken Sound Parkway NW, Suite 300  
Boca Raton, FL 33487-2742

© 2015 by Taylor & Francis Group, LLC  
CRC Press is an imprint of Taylor & Francis Group, an Informa business

No claim to original U.S. Government works  
Version Date: 20150106

International Standard Book Number-13: 978-981-4613-28-6 (eBook - PDF)

This book contains information obtained from authentic and highly regarded sources. Reasonable efforts have been made to publish reliable data and information, but the author and publisher cannot assume responsibility for the validity of all materials or the consequences of their use. The authors and publishers have attempted to trace the copyright holders of all material reproduced in this publication and apologize to copyright holders if permission to publish in this form has not been obtained. If any copyright material has not been acknowledged please write and let us know so we may rectify in any future reprint.

Except as permitted under U.S. Copyright Law, no part of this book may be reprinted, reproduced, transmitted, or utilized in any form by any electronic, mechanical, or other means, now known or hereafter invented, including photocopying, microfilming, and recording, or in any information storage or retrieval system, without written permission from the publishers.

For permission to photocopy or use material electronically from this work, please access [www.copyright.com](http://www.copyright.com) (<http://www.copyright.com/>) or contact the Copyright Clearance Center, Inc. (CCC), 222 Rosewood Drive, Danvers, MA 01923, 978-750-8400. CCC is a not-for-profit organization that provides licenses and registration for a variety of users. For organizations that have been granted a photocopy license by the CCC, a separate system of payment has been arranged.

**Trademark Notice:** Product or corporate names may be trademarks or registered trademarks, and are used only for identification and explanation without intent to infringe.

**Visit the Taylor & Francis Web site at**  
**<http://www.taylorandfrancis.com>**

**and the CRC Press Web site at**  
**<http://www.crcpress.com>**

*To my siblings  
and  
in memory of my parents*



# Contents

<i>Preface</i>	xvii
<i>Principal Symbols</i>	xxi
<i>List of Acronyms</i>	xxix
<b>1 Properties of Radiation</b>	<b>1</b>
1.1 Preamble	1
1.1.1 Planck's Law	11
1.1.2 Stefan-Boltzmann's Law	15
1.1.3 Effective Temperature of a Star	17
1.1.4 Wien's Law	20
1.1.5 Color Temperature	21
1.1.6 Electromagnetic Spectrum	25
1.2 Light Intensity	29
1.2.1 Radiometry	30
1.2.2 Photometry	35
1.2.3 Lambert's Cosine Law	37
1.3 Opto-Electronic System Theory	38
1.3.1 Linear System	39
1.3.2 Transfer Functions of Optical and Opto-Electronics Systems	43
1.4 Image Formation	45
1.4.1 Electro-Optical System	48
1.4.2 Photographic Film	50
1.5 Effects of Atmosphere on the Star Images	51
1.5.1 Absorption	52
1.5.2 Scattering	55
1.5.3 Atmospheric Turbulence	57
1.5.4 Resolving Power of a Telescope	63



1.5.5	Passive Approach to Get over Turbulence Effect	67
1.5.6	Real-Time Correction Technique	72
1.5.6.1	Greenwood frequency	73
1.5.6.2	Adaptive optics system	74
<b>2</b>	<b>Photoelectric Concept</b>	<b>79</b>
2.1	Photoelectric Effect	79
2.2	A Brief Account of Semiconductors	84
2.2.1	Crystal Structure	85
2.2.1.1	Crystal lattice	85
2.2.1.2	Arrangements of space lattice	88
2.2.2	Crystal Defects	89
2.2.2.1	Point defects	90
2.2.2.2	Line defects	92
2.2.2.3	Planar (surface) defects	93
2.2.2.4	Bulk (or volume) defects	94
2.2.3	Energy Bands in Semiconductor	95
2.2.3.1	Bandgap energy	96
2.2.3.2	Periodic potentials	98
2.2.4	Electrical Properties of Semiconductors	101
2.2.4.1	Electron-hole pairs	103
2.2.4.2	Drift current	105
2.2.4.3	Diffusion current	106
2.2.4.4	Mobile charge carrier	107
2.2.5	Electron Distribution in Semiconductors	107
2.2.6	Semiconductor Materials	110
2.2.6.1	Intrinsic semiconductor	110
2.2.6.2	Extrinsic semiconductor	112
2.2.7	Diode	113
2.2.8	Transistor	120
2.2.9	Field-Effect Transistor	125
2.3	Integrated Circuits Technology	128
2.3.1	Fabrication of ICs	128
2.3.1.1	Processing steps	129
2.3.1.2	Types of junction	132
2.3.2	Metal-Oxide Semiconductor Structure	134
2.3.3	Metal-Oxide Semiconductor FET	138
2.4	Operational Amplifier	141

<b>3</b>	<b>Concept of Laser</b>	<b>145</b>
3.1	Introduction	145
3.2	Main Characteristics	146
3.2.1	Coherent Beam	146
3.2.1.1	Temporal coherence	147
3.2.1.2	Spatial coherence	148
3.2.2	Spatial Filter	151
3.2.3	Beam Expansion	154
3.2.4	Output Power	155
3.3	Principles of Emission	156
3.3.1	Induced Absorption	156
3.3.2	Spontaneous Emission	157
3.3.3	Stimulated Emission	160
3.3.4	Population Inversion	162
3.3.5	Emission Line-Width	164
3.3.5.1	Doppler broadening	164
3.3.5.2	Natural broadening	166
3.3.5.3	Collisional broadening	167
3.3.6	Principal Components of a Laser	169
3.3.7	Laser Systems	171
3.3.7.1	Gas lasers	171
3.3.7.2	Dye lasers	173
3.3.7.3	Optically pumped solid-state lasers	173
3.3.8	Semiconductor Diode Laser	175
3.3.8.1	Light-emitting diode	175
3.3.8.2	Laser diode	176
3.4	Fiber-Optics	178
3.4.1	Principle of Operation	178
3.4.1.1	Numerical aperture	180
3.4.1.2	Relative core-cladding index difference	180
3.4.2	Types of Fibers	181
3.4.3	Fiber Laser	183
3.4.4	Applications of Optical Fibers	185
3.4.4.1	Fibers used at telescopes	186
3.4.4.2	Fibers used for interferometry	187
3.4.5	Drawback of fibers	189

3.4.5.1	Absorption loss	189
3.4.5.2	Radiative loss	191
3.4.5.3	Dispersion	192
3.4.5.4	Losses due to miscellaneous sources	195
3.5	Light Sources and Illumination Systems	197
3.5.1	Lens-Based Light Source	197
3.5.2	Laser as a Light Source	200
3.5.3	Laser Interferometer Gravitational-wave Observatory	204
3.5.4	Laser Guide Star	206
<b>4</b>	<b>Photon Detection Process</b>	<b>209</b>
4.1	Radiation Detectors	209
4.1.1	Figure of Merit	211
4.1.1.1	Spectral bandwidth	213
4.1.1.2	Responsivity	214
4.1.1.3	Quantum efficiency	216
4.1.1.4	Detectivity	219
4.1.1.5	Frequency response	220
4.1.1.6	Response time	221
4.1.1.7	Dynamic range	223
4.1.1.8	Dark current	224
4.1.2	Detection of Photoevent	225
4.2	Mechanism of Photon Detection	226
4.2.1	The Human Eye	226
4.2.1.1	Structure of the eye	227
4.2.1.2	Operation of the eye	235
4.2.2	Photography	238
4.2.3	Micro-Photometer	240
4.3	Photon Detectors	241
4.3.1	Photon Effects	242
4.3.1.1	Internal photon effects	244
4.3.1.2	External photon effects	248
4.3.1.3	Other photon effects	248
4.3.1.4	Wave interaction effects	249
4.3.2	General Requirements of an Ideal Detector	251
4.3.2.1	Photocurrent	251
4.3.2.2	Gain	252

4.4	System Analysis	254
4.4.1	Principal Performance Functions	254
4.4.1.1	Limiting resolution	254
4.4.1.2	Non-linearity	255
4.4.1.3	Spectral response	256
4.4.1.4	Field-of-view	256
4.4.2	Limits on Radiation Detector Sensitivity	257
4.5	Noise	258
4.5.1	Radiation Noise	258
4.5.1.1	Photon signal fluctuation limit	259
4.5.1.2	Background photon fluctuation limit	260
4.5.2	Intrinsic Detector Noise	264
4.5.2.1	Thermal noise	264
4.5.2.2	Generation-recombination noise	265
4.5.2.3	Quantum (Shot) noise	266
4.5.2.4	Flicker noise ( $1/f$ -noise)	269
4.5.2.5	Dark current noise	271
4.5.3	Amplifier Noise	272
4.5.4	Read-Out Noise	273
4.5.5	Noise Figure	274
4.5.5.1	Noise accumulation in photoelectric system	277
4.5.5.2	MTF measurements in a photoelectric system	277
<b>5</b>	<b>Photodetectors</b>	<b>279</b>
5.1	Photodetector Elements	279
5.2	Photoemissive Devices	280
5.2.1	Photoemissive Surfaces	283
5.2.1.1	Classical photoemissive surface	283
5.2.1.2	Negative electron affinity photoemissive surface	286
5.2.1.3	Types of photocathodes	288
5.2.2	Photomultiplier	289
5.2.3	Development of PMT	295
5.2.4	Astronomical Applications of PMTs	296
5.2.4.1	Photometer	297
5.2.4.2	Interferometric applications of PMTs	301

5.2.5	Use of Photoemission Devices for High Energies	305
5.2.5.1	PMTs with scintillators detectors and medical applications	307
5.2.5.2	Use of PMTs for gamma-ray astronomy	309
5.2.6	Image Intensifiers	310
5.2.7	Micro-Channel Plate	314
5.3	Photovoltaic Devices	320
5.3.1	P-N Junction Photodiode	320
5.3.2	P-I-N Photodiode	325
5.3.3	Hetero-junction Photodiode	329
5.3.4	Schottky Barrier Photodiode	331
5.3.5	Avalanche Photodiode	334
5.3.6	Phototransistor	339
5.3.7	Photovoltaic Devices for High Energies	340
5.3.7.1	Modern gamma-ray observatories	341
5.3.7.2	Proportional counters and ASTROSAT LAXPC/SSM	342
5.3.7.3	X-ray CCDs and ASTROSAT SXT	344
5.3.7.4	New-generation semiconductors and ASTROSAT CZTI	345
5.4	Photoconductive Detectors	347
5.5	Detector Arrays	350
5.5.1	Focal Plane Arrays	351
5.5.1.1	Quantum well devices	353
5.5.1.2	Super-lattice structure	355
5.5.1.3	Focal plane array architecture	356
5.5.2	Broad Classifications of Detector Array	358
<b>6</b>	<b>Charge Transfer Devices</b>	<b>361</b>
6.1	Introduction	361
6.2	Charge-Coupled Device	362
6.2.1	Principle of Operation	363
6.2.2	CCD Architectures	367
6.2.2.1	Linear array CCD	368
6.2.2.2	Area array CCD	369
6.2.2.3	Scanning images	376

6.2.3	CCD Camera System	378
6.2.3.1	Dewar	378
6.2.3.2	CCD controller	380
6.2.4	Read-Out Procedure	387
6.2.5	Characteristic Features	390
6.2.5.1	Charge transfer efficiency	391
6.2.5.2	Quantum efficiency	392
6.2.5.3	Dynamic range	395
6.2.5.4	Gain	395
6.2.5.5	Responsivity	396
6.2.5.6	Dark current	397
6.2.6	Calibration of CCD	398
6.2.6.1	Sources of non-uniformities	398
6.2.6.2	Flat-field corrections	402
6.3	CMOS Sensor	403
6.4	Intensified CCD	406
<b>7</b>	<b>Photon-Counting Systems</b>	<b>411</b>
7.1	Introduction	411
7.2	Photon-Counting Methods	413
7.2.1	Detection of Photoelectrons	415
7.2.2	Necessity of Photon-Counting Systems	417
7.3	Genesis of Photon-Counting Detectors	419
7.3.1	Initial Experiments	421
7.3.2	Image Photon-Counting Device	422
7.4	PMT-Based Photon-Counting System	423
7.4.1	Digicon	424
7.4.2	Precision Analog Photon Address	425
7.4.3	Position-Sensing Detector	429
7.5	MCP-Based Photon-Counting systems	433
7.5.1	Special Anode Cameras	434
7.5.1.1	Wedge-and-strip anodes detector	434
7.5.1.2	Resistive-anode position sensing detector	435
7.5.2	Multi-Anode Micro-Channel Array	436
7.5.3	Delay-Line Anode	438

7.6	Charge Transfer Device–Based Photon-Counting Systems	441
7.6.1	CP40	441
7.6.2	CMOS-Based Photon-Counting Detector	447
7.7	Solid-State Technologies	449
7.7.1	Low-Light Level CCD	449
7.7.2	Superconducting Tunnel Junction	456
7.7.3	APD-Based Photon-Counting System	457
<b>8</b>	<b>Radiation Detectors for Infrared Wavelengths</b>	<b>461</b>
8.1	Atmospheric Transmission Windows	461
8.2	Infrared Astronomy	464
8.2.1	Ground-Based IR Observations	468
8.2.2	Space-Based IR Observations	471
8.3	Thermal Detectors	472
8.3.1	Thermal Effects	473
8.3.2	General Characteristics of Thermal Detector	475
8.3.3	Bolometers	478
8.3.4	Thermopiles	481
8.3.4.1	Golay cells	481
8.3.4.2	Pyroelectric detectors	482
8.3.5	Thermal Imagers	483
8.4	IR Detectors	485
8.4.1	Evolution of IR Detectors	486
8.4.2	Emerging Trends in IR Detectors	487
8.5	IR Photon Detectors	488
8.5.1	Quantum Well IR Photoconductor	489
8.5.2	Strained-Layer Super-Lattice Detectors	496
8.5.3	Quantum Dot IR Photodetectors	498
8.5.4	Cooled and Uncooled Detectors	499
8.6	IR Imaging Detectors for Astronomy	501
8.6.1	Indium Antimonide Detectors	504
8.6.2	HgCdTe-Based Detectors	508
8.6.2.1	NICMOS	512
8.6.2.2	PICNIC	514
8.6.2.3	HST Wide-field camera	515
8.6.2.4	HAWAII	516
8.6.2.5	SAPHIRA	521

8.7 Heterodyne Interferometry	523
8.7.1 Conventional Heterodyne Detection	525
8.7.1.1 Two-frequency single-photon heterodyne detection	525
8.7.1.2 Two-frequency multi-photon heterodyne detection	526
8.7.2 Non-Linear Heterodyne Detection	529
<i>Appendix</i>	533
<i>Bibliography</i>	535
<i>Index</i>	555





# Preface

Existence of a quantum limit in light detection has led to a quest, on through the last century (and still going on), for the perfect detector that is asymptotically feasible. In 1901, Planck postulated that radiative transfers would occur by discrete packets of energy named “quanta,” following which in 1905, Einstein explained the photoelectric effect. The existence of photons means that for a given collecting area, there exists a physical limit on the minimum light intensity for any observed phenomenon. The perfect detector would be the one that is capable of detecting individual photo-event in the image plane.

The technology of developing detectors has evolved rather fast. The main application of such detectors is in the field of astronomy. Optical telescopes collect the radiation from the faint stellar objects, and the photons received from these objects are feeble. The situation becomes worse in the presence of atmospheric turbulence, particularly in the case of speckle imaging (Labeyrie, 1970) where post-detection data-processing algorithms are required to decipher diffraction-limited spatial Fourier spectrum and image features of such objects. In the early 1970s, the problem was the data processing; computers were not powerful enough for real-time processing and video recorders were expensive. Another application for such detectors is the signal sensing, especially wavefront sensing for adaptive optics (AO) and fringe tracking, which is important for long-baseline optical interferometry.

Research in solid-state electronic imaging detector commenced at the end of the 1960s. Boyle and Smith (1970) introduced the concept of charge-coupled device (CCD). Soon CCDs replaced TV camera tubes for the photon-counting cameras using image intensifiers. However, the possibility to have a fully solid-state photon-

counting camera is quite recent. Modern detectors with (i) high sensitivity, (ii) high selectivity and detectivity, (iii) fast response, (iv) high efficiency, (v) low noise, and (vi) high read-out speed play a key role in astronomical applications. A photon-counting system allows the accurate photon centroiding and provides the dynamic range needed for measurements of source characteristics. At present, the large-format CCD and complementary metal oxide semiconductor array mosaics, electron-multiplication CCDs, electron avalanche photodiode arrays, quantum-well infrared photon detectors, etc., are available. However, the requirements of artifact-free photon shot-noise limited images include higher sensitivity and quantum efficiency, reduced noise that includes dark current, read-out and amplifier noise, smaller point spread functions, and higher spectral bandwidth.

The interest in using the image information in the form of coordinate sets came from the high-angular-resolution techniques (Saha, 1999, 2002, 2007, 2010; Labeyrie et al., 2006, and references therein) for astronomy, which require to take images with exposure times shorter than the atmospheric coherence time (see Section 1.5.3), which is, in general, less than 20 ms depending on the high altitude wind. At this exposure time, the signal-to-noise ratio in each frame is so low that image intensification is usually required. In view of the reasons stated above, I felt the necessity to write a monograph on the modern detector, though a chapter is dedicated on this topic in my first book entitled, *Diffraction-Limited Imaging with Large and Moderate Telescopes*, 2007, World-Scientific. At the fall of 2009, Dr. Stanford Chong, Director and Publisher, Pan Stanford Publishing Co., invited me, for which I am indebted to, for expanding the talk on this topic, which I delivered at AOMD-2008, India, into a book, which I duly complied with to accept the offer. Studded with tens of figures and footnotes, this book aims to address modern detecting systems, technologies and design, evaluation and calibration, control electronics, scientific applications, and results.

The first chapter deals with the fundamentals of important aspects, such as electromagnetic radiations, optical wavelengths in particular, emanating from the celestial sources and their distortions due to the optical elements and Earth's atmosphere while passing

through to the detector. Also, discussed in brief are semiconductor physics and laser and its related phenomena in the second and third chapters, respectively. Chapters 4 through 6 address the photon detection process, photodetectors, and charge transfer devices. The photon-counting devices in the visible wavelength are discussed in the penultimate Chapter 7. The last but not the least, Chapter 8 presents the radiation detectors in infrared wavelengths. My recent interaction with a noted quantum physicist on multi-photon extension of intensity interferometry (Hanbury Brown, 1974) gives me hope that the book would kindle spirits to pursue the fields yet to benefit from the knowledge gained in these chapters. Barring the radio detection technique and intensity interferometry, which were elucidated at length in my second book entitled, *Aperture Synthesis: Methods and Applications to Optical Astronomy*, 2010, Springer, I have also highlighted the detector systems for high energies in brief in Chapters 5 and 7, since their use in astronomy as well as in medical sciences is noteworthy.

I am indebted to my PhD supervisor, late Prof. A. K. Sen, who initiated me into experimental science at the Institute of Radio Physics and Electronics, University of Calcutta. I express my gratitude to A. Labeyrie, S. K. Sarkar, A. Satya Narayanan, Kavita S. Rao, B. P. Pal, R. Ghosh, S. P. Bagare, S. S. Negi, R. Ramesh, M. S. Sundararajan, R. Srinivasan, and U. S. Kamath for assistance as readers of the draft chapters. Thanks are also due to G. P. Weigelt, R. Osterbart, I. S. McLead, A. Popowicz, S. Pal, Ya-Lin Wu, F. Malbet, P. Nisenson (late), V. Chinnappan, N. K. Rao, L. Close, S. Morel, A. Blazit, E. Pedretti, D. Mourard, D. Ives, K. B. Jinesh, N. Bezawada, A. R. Rao, J. Chatterjee, S. Ghosh, S. Srivastav, G. C. Anupama, D. Ojha, and S. Bhadra for providing the images, spectra, figures, etc., and granting permission for their reproduction. The services rendered by Baba A. Varghese, A. Surya, R. K. Sharma, S. P. Tewari, V. Valsan, R. Mondal, P. Anbazhagan, and S. K. Dhara are greatly acknowledged.

## References

- Boyle W. S. Smith G. E., 1970, *Bell System Tech. J.*, **49**, 587.  
 Hanbury Brown R., 1974, *The Intensity Interferometry: Its Applications to Astronomy*, Taylor & Francis, London.

- Labeyrie A., 1970, *Astron. Astrophys.*, **6**, 85.
- Labeyrie A., Lipson S. G., Nisenson P., 2006, *An Introduction to Optical Stellar Interferometry*, Cambridge University Press, UK.
- Saha S. K., 1999, *Bull. Astron. Soc. Ind.*, **27**, 443.
- Saha S. K., 2002, *Rev. Mod. Phys.*, **74**, 551.
- Saha S. K., 2007, *Diffraction-limited Imaging with Large and Moderate Telescopes*, World-Scientific, New Jersey.
- Saha S. K., 2010, *Aperture Synthesis: Methods and Applications to Optical Astronomy*, Springer, New York.

**Swapan K. Saha**  
November 2014

## Principal Symbols

$A_{21}$	Einstein coefficient for spontaneous emission
$A_d$	Effective area of the detector
$\mathbf{B}(\mathbf{r}, t)$	Time dependent magnetic field
$B_{21}$	Einstein coefficient for stimulated emission
$B_\nu(T)$	Spectral radiance
$\mathcal{B}_n(\mathbf{r})$	Covariance function
$C$	Capacitance
$C$	Coulomb
$C_n^2$	Refractive index structure constant
$D$	Diameter of the aperture
$D^*$	Specific detectivity
$D_e$	Diffusion coefficient of electrons
$D_h$	Diffusion coefficient of holes
$\mathbf{D}$	Electric displacement vector
$\mathcal{D}_n(\mathbf{r})$	Refractive index structure function
$E_C$	Conduction band energy
$E_D$	Donor level energy
$\mathcal{E}_e$	Irradiance
$\mathcal{E}_e(\lambda)$	Spectral irradiance
$E_F$	Fermi level energy
$E_g$	Bandgap energy
$E_i$	Intrinsic Fermi level energy
$E_k$	Kinetic energy
$\mathcal{E}_v$	Illuminance
$erfc$	Error function
$\mathbf{E}(\mathbf{r}, t)$	Time dependent electric field
$E_V$	Valence band energy

$F$	Flux
$f$	Focal length
$f_e$	Effective focal length
$f_G$	Greenwood frequency
$F_{\max}$	Maximum frame rate
$F_{\#}$	Aperture ratio
$G$	Gain
$\mathcal{G}$	Heat conductance
<b>H</b>	Magnetic field
$\mathcal{H}$	Heat capacity
$\hat{H}$	Hamiltonian operator
$\hbar(= h/2\pi)$	Reduced Planck constant
$I$	Intensity of light
$i$	Current
$i_B$	Base current
$i_C$	Collector current
$i_D$	Dark current
$i_d$	Detector current
$I_{DC}$	Direct current
$i_e$	Electron current
$i_E$	Emitter current
$\mathcal{I}_e$	Radiant intensity
$i_{FN}$	Flicker noise current
$i_h$	Hole current
$\mathcal{I}_\lambda$	Spectral radiant intensity
$\mathcal{I}_v$	Luminous intensity
$i_n$	Dark current noise
$i_{ph}$	Photocurrent
$i_Q$	Shot-noise or quantum noise
$i_s$	Signal current
$i_{sc}$	Short-circuit signal current
$i(t)$	instantaneous photocurrent
$i_0$	Reverse saturated current
$\hat{I}(\mathbf{u})$	Image spectrum
$\hat{I}(\mathbf{x})$	Intensity distribution at the image plane
<b>J</b>	Electric current density
$J_d$	Drift current

$\mathbf{J}_{\text{diff}}$	Diffusion current
$j$	= 1, 2, 3
$L_e$	Diffusion length of electrons
$L_h$	Diffusion length of holes
$L_0$	Outer scale length
$l$	Characteristic size of viscous fluid
$l_c$	Coherence length
$l_0$	Inner scale length
$\mathcal{L}_e$	Radiance
$\mathcal{L}_v$	Luminance (brightness)
$\mathcal{L}_\star$	Stellar luminosity
$M$	Multiplication factor
$M$	Magnification
$\mathcal{M}_e$	Radiant emittance
$\mathcal{M}_e$	Spectral radiant emittance
$\mathcal{M}_v$	Luminous emittance
$\mathcal{M}_q$	Photon emittance
$\mathcal{M}_q(\lambda)$	Spectral photon emittance
$m_v$	Apparent visual magnitude
$M_v$	Absolute visual magnitude
$m^*$	Effective mass
$M_\star$	Stellar mass
$n$	Refractive index
$N$	Integer value
$N_e$	Magnitude of free electron concentration
$N_h$	Magnitude of hole concentration
$N_{\text{pe}}$	Number of photoelectrons
$N_{\text{ph}}$	Number of photons
$n_{\text{ro}}$	Read-out noise
$n(\mathbf{r}, t)$	Refractive index of the atmosphere
$O(\mathbf{x})$	Object illumination
$\widehat{O}(\mathbf{u})$	Object spectrum
$P$	Pressure
$\mathcal{P}$	Probability distribution
$\mathbf{p}$	Momentum
$P_o$	Output optical power
$P_0$	Incident optical power



$q$	Electron charge
$Q_e$	Radiant energy
$Q_\lambda$	Spectral radiant energy
$Q_\nu$	Luminous energy
$\mathbf{r}(= x, y, z)$	Position vector of a point in space
$R$	Resistance
$\mathcal{R}$	Responsivity
$\mathcal{R}(\lambda)$	Spectral responsivity
$\mathcal{R}_\nu$	Luminous flux responsivity
$Re$	Reynolds number
$R_f$	Entrance face reflectivity (Fresnel reflectivity)
$R_H$	Rydberg constant
$r_0$	Fried's parameter
$R_\star$	Stellar radius
$\hat{\mathbf{s}}$	Unit vector
$S(\mathbf{x})$	Point spread function
$\mathcal{S}_r$	Strehl's ratio
$\langle \hat{S}(\mathbf{u}) \rangle$	Transfer function for long-exposure image
$\hat{S}(\mathbf{u})$	Optical transfer function
$ \hat{S}(\mathbf{u}) ^2$	Modulus transfer function
$sr$	Steradian
$s(\lambda)$	Spectral response of the detector
$t$	Time
$t(x, y)$	Transmittance
$T$	Temperature
$\mathbf{u} = (u, v)$	Spatial frequency vector
$V$	Electrostatic potential
$\mathcal{V}$	Visibility
$v_a$	Average velocity of a viscous fluid
$V_{br}$	Breakdown voltage
$v_d$	Drift velocity
$v_g$	Group velocity
$V_{oc}$	Open-circuit voltage
$v_p$	Phase velocity
$w$	Width of depletion region
$\mathcal{W}$	Radiation power
$\mathbf{x}(= x, y)$	Two-dimensional (2-D) position vector
$Z_j(\rho, \theta)$	Zernike polynomial of order $j$

**Greek symbols**

$\alpha$	Extinction coefficient
$\alpha_e$	Electron-ionization coefficient
$\alpha_h$	Hole-ionization coefficient
$\beta$	Ratio of electron and hole mobilities
$\gamma$	Zenith angle
$\Gamma(\tau)$	FT of auto-correlation function
$\delta$	Phase difference
$\delta(x)$	Dirac delta function
$\Delta$	Relative core-cladding index difference
$\Delta\nu$	Spectral width
$\Delta f$	Electrical bandwidth
$\Delta t$	Integration time
$\epsilon_0$	Permittivity in vacuum
$\varepsilon$	Energy dissipation
$\eta_d$	Quantum efficiency of the detector
$\Theta$	Seebeck coefficient
$\theta$	Angular diameter
$\theta_0$	Isoplanatic angle
$(\theta, \phi)$	Polar coordinates
$\kappa$	Wave number
$\boldsymbol{\kappa}$	Wave vector
$\lambda$	Wavelength
$\lambda_0$	Wavelength in vacuum
$\mu_0$	Permeability in vacuum
$\mu_e$	Electron mobility
$\mu_h$	Hole mobility
$\nu$	Frequency
$\boldsymbol{\xi}(\xi, \eta)$	2-D position vector
$\langle\sigma\rangle$	Standard deviation
$\langle\sigma\rangle^2$	Variance
$\sigma_1$	Scintillation index
$\tau_0$	Atmospheric coherence time
$\tau_c$	Coherence time
$\tau_d$	Response time
$\tau_e$	Lifetime of electrons
$\tau_g$	Group delay

$\tau_h$	Lifetime of holes
$\tau_r$	Total rise time
$\tau_{RC}$	RC time-constant
$\tau_w$	Delay time due to waveguide dispersion
$\phi_0$	Work function
$\phi_m$	Work function of metal
$\phi_s$	Work function of semiconductor
$\Phi_e$	Radiant power/flux
$\Phi_\lambda$	Spectral radiant flux
$\Phi_v$	Luminous power/flux
$\Phi_n(\boldsymbol{\kappa})$	Power spectral density
$\chi$	Electron affinity
$\Psi$	Time-dependent wave-function
$Psi_B$	Potential difference between $E_F$ and $E_i$
$\Psi_n$	Eigen functions
$\Omega$	Solid angle
$\omega$	Angular frequency
*	Complex operator
★	Convolution operator
⊗	Correlation
⟨ ⟩	Ensemble average
$\hat{\phantom{x}}$	Fourier transform operator
$\nabla$	Linear vector differential operator
$\nabla^2$	Laplacian operator

### Some numerical values of physical and astronomical constants

---

$c$	Speed of light in free space	$3 \times 10^8 \text{ m.s}^{-1}$
$c_1$	First radiation constant	$2\pi hc^2 = 3.7418 \times 10^4$ $\text{W}\mu\text{m}^4.\text{cm}^{-2}$
$c_2$	Second radiation constant	$hc/k_B = 1.4388 \times 10^4 \mu\text{m K}$
eV	Electron volt	$1.60 \times 10^{-19} \text{ J}$
$h$	Planck's constant	$6.626096 \times 10^{-34} \text{ J.s}$
$Jy$	Jansky	$10^{-26} \text{ W m}^{-2} \text{ Hz}^{-1}$
$k_B$	Boltzmann's constant	$1.380662 \times 10^{-23} \text{ J.K}^{-1}$
$K_m$	Luminous efficacy (photopic vision)	$683 \text{ lm.W}^{-1}$
$\mathcal{L}_\odot$	Solar luminosity	$3.839 \times 10^{26} \text{ W}$
lx	Lux	$\text{lm.m}^{-2}$
$M_\odot$	Solar mass	$1.9889 \times 10^{30} \text{ kg}$
$q$	Elementary charge	$1.6 \times 10^{-19} \text{ C}$
$R_L$	Load resistance	
$R_\odot$	Solar radius	$6.96 \times 10^8 \text{ m}$
$T_\odot$	Solar effective temperature	$5780 \text{ K}$
$\epsilon_0$	Permittivity constant	$8.8541 \times 10^{-12} \text{ F.m}^{-1}$
$\mu_0$	Permeability constant	$1.26 \times 10^{-6} \text{ H.m}^{-1}$
$\sigma$	Stefan-Boltzmann's constant	$5.67 \times 10^{-8} \text{ W m}^{-2} \text{ K}^{-4}$

---



## List of Acronyms

AC	Alternating current
ACT	Atmospheric Cerenkov Telescope
A/D	Analog-to-digital
AGN	Active galactic nuclei
AMBER	Astronomical Multiple BEam Recombiner
AO	Adaptive optics
APD	Avalanche photodiode
ASM	Adaptive secondary mirror
ASTROSAT	ASTROnomy SATellite
AT	Auxiliary Telescope
AU	Astronomical unit
BID	Blind iterative deconvolution
BJT	Bipolar junction transistor
BLIP	Background-limited performance
CCD	Charge coupled device
<i>cd</i>	Candela
CDS	Correlated double sampling
CHARA	Center for High Angular Resolution Astronomy
CIC	Clock-induced charge
CMOS	Complementary metal oxide semiconductor
CP40	Comptage de photon 40 mm
CPNG	Comptage de photon nouvelle génération
CPU	Central processing unit
COAST	Cambridge Optical Aperture Synthesis Telescope
CRT	Cathode ray tube
CS	Curvature sensor
CTE	Charge transfer efficiency
CTF	Contrast transfer function
CZT	Cadmium zinc telluride

CZTI	Cadmium zinc telluride imager
dB	Decibel
DC	Direct current
DM	Deformable mirror
DSP	Digital signal processor
EELT	European Extremely Large Telescope
EMCCD	Electron multiplying CCD
EMF	Electromotive force
ESA	European Space Agency
ESO	European Southern Observatory
FET	Field-effect transistor
FLUOR	Fiber-Linked Unit for Optical Recombination
FOV	Field-of-view
FPA	Focal plane array
FPGA	Field programmable gate array
FPS	Frames per second
FT	Fourier transform
FUSE	Far-Ultraviolet Spectroscopic Explorer
FWHM	Full width at half maximum
GALEX	Galaxy Evolution Explorer
G-APD	Geiger-mode APD
GI2T	Grand Interféromètre à deux Télescopes
GR	Generation-recombination
GRAVITY	General relativity analysis via VLT interferometry
HAGAR	High Altitude Gamma ray telescope ARray
HR	Hertzsprung-Russell
HAWAII	HgCdTe Astronomical Wide Area Infrared Imager
HCT	Himalayan Chandra Telescope
HST	Hubble Space Telescope
Hz	Hertz
IAO	Indian Astronomical Observatory
IC	Integrated circuit
ICCD	Intensified CCD
IF	Intermediate frequency
IO	Integrated optics
IONIC	Integrated optics near-IR combiner
IOTA	Infrared Optical Telescope Array

IPCS	Image Photon-Counting System
IR	Infrared
IRAF	Image Reduction and Analysis Facility
IRAS	InfraRed Astronomical Satellite
IRTS	InfraRed Telescope in Space
ISI	Infrared Spatial Interferometer
ISM	Interstellar medium
ISO	Infrared Space Observatory
I2T	Interféromètre à deux Télescopes
ITF	Intensity transfer function
kV	Kilovolt
Laser	Light amplification by stimulated emission of radiation
LBOI	Long-baseline optical interferometry
LBT	Large Binocular Telescope
LBV	Luminous blue variable
LCD	Liquid crystal display
LED	Light-emitting diode
LGS	Laser guide star
LHS	Left hand side
LIGO	Laser Interferometer Gravitational-Wave Observatory
LSF	Line spread function
LO	Local oscillator
L3CCD	Low light level CCD
LWIR	Long-wave infrared
ly	Light year
mA	Milli-ampere
MAMA	Multi Anode Micro-channel Array
mas	Milliarcseconds
Maser	Microwave amplification by stimulated emission of radiation
MBE	Molecular beam epitaxy
MCP	Micro-channel plate
MCT	Mercury cadmium telluride
MHz	Megahertz
MIRC	Michigan Infra-Red Combiner
MMDM	Micro-machined DM
MMF	Magnetomotive force
MO	Microscope objective



MOS	Metal-oxide semiconductor
MOSFET	Metal-oxide semiconductor FET
MOSFIRE	Multi-Object Spectrometer for InfraRed Exploration
MMT	Multi Mirror Telescope
MRI	Magnetic resonance imaging
MSGIS	Mammary Gland Specific Gamma Imaging System
MTF	Modulation transfer function
MWIR	Mid-wave infrared
NA	Numerical aperture
NASA	National Aeronautics and Space Administration
NEA	Negative electron affinity
NEAT	Nearby Earth Astrometric Telescope
NE $\Delta$ T	Minimum detectable temperature difference
NEP	Noise equivalent power
NETD	Noise equivalent temperature difference
NICMOS	Near Infrared Camera and Multi-Object Spectrometer
NIRSPEC	Near Infrared echelle Spectrometer
nm	Nanometer
OCT	Optical coherence tomography
Op-Amp	Operational amplifier
OPD	Optical path difference
OTF	Optical transfer function
PAPA	Precision Analog Photon Address
PAVO	Precision Astronomical Visible Observations
pc	Parsec
PC	Photoconductive
PDS	Photometric data system
PE	Photoemissive
PEM	Photoelectromagnetic
PHD	Pulse height distribution
pixel	PICTure ELeMent
PMT	Photomultiplier tube
POSS	Palomar Observatory Sky Survey
PSD	Position-sensing device
PSF	Point spread function
PSPMT	Position sensitive photomultiplier technology
PTF	Phase transfer function
PV	Photovoltaic

PZT	Piezo-electric transducer
QE	Quantum efficiency
QDIP	Quantum dot IR photodetector
QWIP	Quantum well IR photodetector
RHS	Right hand side
RMS	Root-mean-square
ROIC	Read-out integrated circuit
SAO	Special Astrophysical Observatory
SH	Shack-Hartmann
SL	Super-lattice
SLS	Strained layer super-lattice
S/N	Signal-to-noise
<i>sr</i>	Steradian
STJ	Superconducting tunnel junction
SUSI	Sydney University Stellar Interferometer
SWIR	Short-wave infrared
SXT	Soft X-ray Telescope
TC	Triple-correlation
TDI	Time-delay and integration
TMT	Thirty Meter Telescope
TSM	Tomographic speckle imaging
TV	Television
UT	Unit Telescope
UV	Ultra-violet
UVIT	Ultra-Violet Imaging Telescope
VBO	Vainu Bappu Observatory
VBT	Vainu Bappu Telescope
VEGA	Visible spEctroGraph and polArimeter
VINCI	VLT INterferometer Commissioning Instrument
VLTI	Very Large Telescope Interferometer
WFS	Wavefront sensor